



CHEVERNY SMALL SCONCE + SMALL, MEDIUM & EXTRA-LARGE VANITIES

LXW1061; LXV1001; LXV1002; LXV1004



General Product Information



Suggested/Required Tools




Safety Information



FIXTURE PARTS

- A. Junction box
- B. Hot Power Line Wire
- C. Neutral Power Line Wire
- D. Ground Wire
- E. Hot Fixture Wire
- F. Neutral Fixture Wire
- G. Fixture Ground Wire
- H. Wire Nuts
- I. Backplate (Fixture Base & Mounting Plate)
- J. Fixture Screws
- K. Socket
- L. Bulb(s) (Not Included)
- M. Studs
- N. Washers
- O. Cap Nuts
- P. Shade(s)



INSTRUCTIONS

I. Preparing the Fixture

1. Separate the mounting plate from the fixture base/backplate by removing the fixture screws.
2. Install the mounting plate to the junction box and secure it using mounting or anchor screws (LXW1061 uses two anchor screws).

II. Wiring the Fixture

1. Safety first! Locate the circuit breaker and switch it off to cut off the power supply to the relevant circuits to ensure there's no electricity running through the wiring.
2. In accordance with local electrical codes, connect the fixture ground wire (bare copper or silver wire) to suitable ground. This may be a green ground screw on the mounting plate, which the ground wire should be tightly wrapped around or a house wire (green or bare copper wire without insulation).
3. Twist the bare ends of the following pairs of wires together using a wire nut to secure a connection:
 - a) Hot fixture wire (black) and hot power line wire from the junction box (hot to hot)
 - b) Neutral fixture wire (white) and neutral power line wire from the junction box (neutral to neutral)
4. Carefully tuck all the wires behind the mounting plate into the junction box.

III. Installing the Fixture

1. Mount the fixture onto the mounting plate and secure it in place by tightening the fixture screws.
2. Screw the bulb(s) into the socket(s). Refer to the socket label(s) for max wattage information.
3. Using the provided studs, washers, and cap nuts, attach the shade(s) to the fixture.