



CRYSTORAMA LIGHTING



Crystorama.com


ASSEMBLY INSTRUCTION MODEL #ARC-1908-SA-CL-MWP



WARNING:




Electrical Danger



Turn Power Off

All electrical components must be installed by a licensed electrician in accordance with the National Electric Code and the appropriate local electrical codes.



You will need 8 Candelabra Base Bulb
40 Watts Recommended 60 Watts Max.
USE LED BULBS FOR EXTENDED USE
This fixture is Dry rated

How to Install

1. Please place the fixture parts on a soft-cloth covered platform before installation. Do a complete inventory of all parts and components before you start installing.
2. Insert a scroll onto the top of each arm and secure using the provided screw and wrench.
3. Screw the top stem onto the top of the fixture .
4. Open the quick link at the end of the chain and fasten the chain to the fixture loop. Fasten mounting hardware to junction box with the machine screws. After the wires are connected, screw the screw collar loop onto the nipple. Place the canopy up against the ceiling and secure by tightening the screw collar loop ring.
5. After safely attaching the fixture onto the junction box, install the bulbs and proceed to connecting the power.
6. When you begin to dress the fixture, start with package labeled(A).
7. IMPORTANT: Apply crystal sets in alphabetical order.

****Ensure the 4-hole jewel is positioned at the end installing to the candle cup.**

Crystal Sets

- A. 8sets 35*14mm(2hole)+1*14mm (4hole)
- B. 8sets 18*14mm(2hole)
- C. 1set 21*14mm(2hole)+1*76mm drop
- D. 1set 22*14mm(2hole)+1*76mm drop
- E. 1set 23*14mm(2hole)+1*76mm drop
- F. 1set 24*14mm(2hole)+1*76mm drop
- G. 1set 25*14mm(2hole)+1*76mm drop
- H. 1set 26*14mm(2hole)+1*76mm drop
- I. 1set 27*14mm(2hole)+1*76mm drop
- J. 1set 28*14mm(2hole)+1*76mm drop
- K. 1set 29*14mm(2hole)+1*76mm drop
- L. 8sets 2*14mm(2hole)
- M. 8sets 2*14mm(2hole)+1*76mm drop



WARNING: This product can expose you to Lead, which is known to the State of California to cause cancer and/or birth defects or reproductive harm. For more information go to www.P65Warnings.ca.gov



PART NUMBER MODEL #ARC-1908-SA-CL-MWP

Part Number

Part Numbers

- A. (1)-Mounting Hardware
- B. (1)-Canopy;ø5*H1"
(XBN1905SACAN5.375IN)
- C. (1)-Screw Collar Loop Ring
- D. (1)-Screw Collar Loop
- E. (1)-Chain;L72"
(XBN1905SACHA4MM)
- F. (1)-Fixture Loop;ø2"
- G. (1)-Top Stem;L4"
- H. (8) - Candle Sleeve;L2 4/5"
(XBN1902SACDL2.8IN)
- I. (1)-Finial;H1 1/5" (XBN1900SAFIN)
- J. (8)-Scroll

